



### \* Headset

- Charge by Adaptor
- Battery Level
- Charging and Operation Time
- Wearing Your Headset

**Package Include**

- Bluetooth headset
- Ear Hook
- AC Charger
- Additional ear rubber
- User Manual

### 1 Power On/Off

**Power ON:** Press and hold the Multi-Function Button for 2 sec. until both BlueLED flash then release it. (Turn on melody)

**Power Off:** Press and hold the Multi-Function Button for 4 sec. until both BlueLED flash then release it. (Turn off melody)

### 2 Pairing

Before you use headset, please pair your headset with mobile phone first.

Ensure your headset is turned off.

Press and hold the Multi-Function Button for 5 sec. until right and left BlueLED flash. (Pairing Melody)

### 3 Making a call

1. Last number dial
2. Press Multi-Function button shortly.
3. Select number and press multi-function button shortly.
4. Voice Dial
5. Press and hold Multi-Function button for 2 sec. until you hear beep twice then release the button.

### 4 Answering a call

Press Multi-Function button shortly to receive call.

### 5 Reject an incoming call

Press and hold Multi-Function button for 2 sec until beep twice. Then release the button to reject an incoming call.

### 6 Ending a call

Press Multi-Function button shortly while you are on the line. You can also ending a call from your mobile by push "END" button.

### 7 Transferring a call

Headset mode phone: Press and hold Multi-Function button for 2 sec until beep twice. Headset mode mobile: Press and hold Multi-Function button for 2 sec until you hear beep twice.

### 8 Volume control

Adjust speaker volume by pushing volume up or down button which is located on the right and left side of headset.

### 9 Mic mute

Press and hold volume down button for 2 sec. then the MIC mute will be activated. You can hear the status indication melody every 10 sec. in MIC mute mode. You can deactivate the MIC mode by pushing volume up or down button at once.

### 10 Call waiting (3way calling)

Before you use 3way calling function, please make sure that your mobile phone supports "headset mode". And please check with your network operator if they support Call Hold & Multiparty call service.

### 11 Missing call alert

When there is a missing call, you will hear sound every 10 sec. for 10 min. You can release alarm beep by push button.

### 12 Multipoint Function

The headset unit supports simultaneous connection with 2 mobile phones with full control of each call.

### 13 Audio Caller ID

You can hear the melody and the Caller ID(Caller's number) from the headset for an incoming call. It can be activated or deactivated by pushing and holding Volume Up & Down button for 2 sec.

### 14 RESET OF THE HEADSET

Press and hold Multi-Function button & Volume Down button for 4 sec. Then all device information and call list of your headset will reset.

### 15 Safety and General Information

### 16 FCC & IC STATEMENT

### 17 EU

### 18 Warranty

### 19 WEEE Symbol Information

### \* Headset Laden

### \* Tragen

**Packungsinhalt**

- Bluetooth-Headset
- Alte Ohrhörer
- zusätzliche Ohrschäume
- Bedienungsanleitung

### 1 EIN-AUSSCHALTEN

### 2 PAARUNG

### 3 EINEN ANRUF TÄTIGEN

### 4 EINEN ANRUF ANNEHMEN

### 5 EINEN ANRUF ABLEHNEN

### 6 EINEN ANRUF BEENDEN

### 7 EINEN ANRUF WEITERLEITEN

### 8 LAUTSTÄRKE ANPASSEN

### 9 DAS MIKROFON STUMM SCHALTEN

### 10 ANRUF IN WARTESCHLANGE (Konferenzschaltung)

### 11 VERPASTER ANRUF

### 12 Multipoint-Funktion

### 13 Akustische Anzeige der Rufnummer-Identifikation (Audio Caller ID)

### 14 ZURÜCKSETZEN DER FREISPRECHFUNKTION

### 15 Sicherung und allgemeine Informationen

### 16 Garantie

### 17 WEEE Symbol Information

Korrekte Entsorgung dieses Produkts (Elektromüll)

### 18 Garantie

### 19 WEEE Symbol Information

Korrekte Entsorgung dieses Produkts (Elektromüll)

### \* Oreillette

### \* Porter le headset

**Le coffret comprend**

- Oreillette gauche
- Oreillette droite
- Chargeur CA
- Pratiquer amovible supplémentaire
- Manuel d'utilisation

### 1 Eteindre / Allumer

### 2 Paillage

### 3 Passer un appel

### 4 Répondre à un appel

### 5 Rejeter un appel en attente

### 6 Terminer un appel

### 7 Transférer un appel

### 8 Volume

### 9 Micro en sourdine

### 10 Appel en attente (conférence à 3)

### 11 Signal d'appel en absence

### 12 Fonction multiconférence

### 13 Identification d'appel par la voix (Audio Caller ID)

### 14 REINITIALISATION DE L'OREILLETTE

### 15 CONSIGNES DE SÉCURITÉ ET INFORMATIONS GÉNÉRALES

### 16 Garantie

### 17 WEEE Symbol Information

Comment éliminer ce produit (déchets d'équipements électriques et électroniques)

### 18 Garantie

### 19 WEEE Symbol Information

Comment éliminer ce produit (déchets d'équipements électriques et électroniques)

### \* Auricular

### \* Cómo cargar un auricular

### \* Instalación

**El paquete incluye**

- Auricular izquierdo
- Garcho auricular
- Cargador de gama
- Auricular de gama adicional
- Manual del usuario

### 1 Encendido/Apagado

### 2 Emparejamiento

### 3 Cómo realizar una llamada

### 4 Contestación de llamadas

### 5 Rechazar una llamada entrante

### 6 Cómo finalizar una llamada

### 7 Transfencia de llamadas

### 8 Control del volumen

### 9 Micrófono mudo

### 10 Llamada en espera (llamada en conferencia)

### 11 Alerta de llamada perdida

### 12 Función multipuntos

### 13 Información de informe sobre el llamador por la voz

### 14 REINICIAR EL AURICULAR

### 15 Información General y de Seguridad

### 16 Garantía de calidad del producto

### 17 WEEE Symbol Information

Eliminación correcta de este producto (material eléctrico y electrónico de desecho)

### 18 Garantía de calidad del producto

### 19 WEEE Symbol Information

Eliminación correcta de este producto (material eléctrico y electrónico de desecho)